




WEBENCH® Design Report







Design : 3601799/9 LP38693SD-2.5/NOPB
LP38693SD-2.5/NOPB 5.0V-5.0V to 2.5V @ 0.5A






Electrical BOM

#	Name	Manufacturer	Part Number	Properties	Qty	Price	Footprint
1.	Cin	TDK	C1005X5R0J105M Series= X5R	Cap= 1.0 µF ESR= 7.9 mOhm VDC= 6.3 V IRMS= 0.0 A	1	\$0.01	0402 8mm2
2.	Cout	TDK	C1005X5R0J105M Series= X5R	Cap= 1.0 µF ESR= 7.9 mOhm VDC= 6.3 V IRMS= 0.0 A	1	\$0.01	0402 8mm2
3.	Renable	Vishay-Dale	CRCW040210K0FKED Series= CRCW..e3	Res= 10.0 kOhm Power= 63.0 mW Tolerance= 1.0%	1	\$0.01	0402 8mm2
4.	U1	Texas Instruments	LP38693SD-2.5/NOPB	Switcher	1	\$0.50	SDE06A 25mm2







Operating Values

#	Name	Value	Category	Description
1.	IC Iground	55.0 μ A	Current	IC ground current
2.	Iin Avg	500.06 mA	Current	Average input current
3.	BOM Count	4	General	Total Design BOM count
4.	FootPrint	48.0 mm ²	General	Total Foot Print Area of BOM components
5.	IC Tolerance	125.0 mV	General	IC Feedback Tolerance
6.	Pout	1.25 W	General	Total output power
7.	Total BOM	\$0.53	General	Total BOM Cost
8.	Vin p-p	50.0 mV	Op_point	Input Source ripple voltage
9.	Efficiency	49.995 %	Op_point	Steady state efficiency
10.	IC Tj	91.263 degC	Op_point	IC junction temperature
11.	ICThetaJA	49.0 degC/W	Op_point	IC junction-to-ambient thermal resistance
12.	IOUT_OP	500.0 mA	Op_point	Iout operating point
13.	Input Ripple Frequency	100.0 kHz	Op_point	Input Source Ripple Frequency for PSRR Calculation
14.	PSRR est.	-51.76 dB	Op_point	Power Supply Rejection Ratio estimated
15.	VIN_OP	5.0 V	Op_point	Vin operating point
16.	Vout p-p	129.113 μ V	Op_point	Peak-to-peak output ripple voltage
17.	IC Pd	1.25 W	Power	IC power dissipation
18.	Total Pd	1.25 W	Power	Total Power Dissipation

Design Inputs

#	Name	Value	Description
1.	Iout	500.0 mA	Maximum Output Current
2.	Iout1	500.0 mAmps	Output Current #1
3.	VinMax	5.0 V	Maximum input voltage
4.	VinMin	5.0 V	Minimum input voltage
5.	Vout	2.5 V	Output Voltage
6.	Vout1	2.5 Volt	Output Voltage #1
7.	base_pn	LP38693	Base Product Number
8.	source	DC	Input Source Type
9.	Ta	30.0 degC	Ambient temperature

Design Assistance

1. **LP38693** Product Folder : <http://www.ti.com/product/lp38693> : contains the data sheet and other resources.

Texas Instruments' WEBENCH simulation tools attempt to recreate the performance of a substantially equivalent physical implementation of the design. Simulations are created using Texas Instruments' published specifications as well as the published specifications of other device manufacturers. While Texas Instruments does update this information periodically, this information may not be current at the time the simulation is built. Texas Instruments does not warrant the accuracy or completeness of the specifications or any information contained therein. Texas Instruments does not warrant that any designs or recommended parts will meet the specifications you entered, will be suitable for your application or fit for any particular purpose, or will operate as shown in the simulation in a physical implementation. Texas Instruments does not warrant that the designs are production worthy.

You should completely validate and test your design implementation to confirm the system functionality for your application prior to production.

Use of Texas Instruments' WEBENCH simulation tools is subject to [Texas Instruments' Site Terms and Conditions of Use](#). Prototype boards based on WEBENCH created designs are provided AS IS without warranty of any kind for evaluation and testing purposes and are subject to the terms of the [Evaluation License Agreement](#).