## **DSSM Mass Erase and Factory Reset**

1.	Open Ta	arge	et Config	guratic	ons			
	CCS_Mis	ic - Co	de Compos	er Studio				
	<u>File</u> <u>E</u> dit	View	Navigate	Project	Run	Scripts	Window	Help
	: 📬 🕶 🔛	Ø	Resource Ex	plorer				100
	Project	Ø	Resource Ex					
		3	Getting Star	ted				
	· 2 · · · ·	V	CCS App Ce	nter				
		0	GUI Compo	ser™			>	
		B	Project Expl	orer				
		8	Problems					
			Console			Alt+S		
		0	Advice					
		莽	Debug					
		0	Memory Bro	owser				
		1010	Registers					
		କୁଟ୍ଲ	Expressions					
		(×)=	Variables			Alt+S	hift+Q, V	
		<b></b>	Disassembly	1				
		•	Breakpoints			Alt+S	hift+Q, B	
		=	Modules					
		<b>P</b>	Terminal					
		1	Scripting Co	nsole				
		2	Target Confi	gurations	N			
		8	Outline		43	Alt+S	nift+Q, O	
		-	Stack Usage					
		-	Memory All	ocation				
		1	Optimizer A	ssistant				
			Other			Alt+SI	hift+Q, Q	

2. In the *Target Configurations* window, find your current MSPM0 project and expand the folders to find the .ccxml file:



3. Right-click the .ccxml file and click on Launch Selected Configuration



 Click on Scripts → MSPM0G3507 Commands → MSPM0\_MailboxMassErase/MSPM0\_MailboxFactoryReset

😚 C	CS_Wo	orkspace	e_11_1_F	lashLoa	der - Sou	irce not f	ound Co	de Composer S	tudio				
<u>F</u> ile	Edit	<u>V</u> iew	<u>P</u> rojec	t <u>T</u> ools	<u>R</u> un	Scripts	<u>W</u> indow	<u>H</u> elp					_
<b>_</b>	• 🛛				7. P	M	SPM0G3507	7 Commands	>	N	ISPM0_MailboxMassErase	D	Þ
to Debug 🛛								MSPM0_MailboxFactoryReset					
V 💱 MSPM0G3507.ccxml [Code Composer Studio - Device Debugging]													
	<i>"</i> ® Т	exas Ins	trument	s XDS11	0 USB De	bug Prol	be/CORTEX	_M0P (Disconn	ected :	Unknow	n)		

5. The console window will show the following and ask user to press the reset button:

Console 
 MSPM0G3507.ccxml

 CS\_DAP\_0: GEL Output: Attempting CS\_DAP connection
 CS\_DAP\_0: GEL Output: Attempting SEC\_AP connection
 CS\_DAP\_0: GEL Output: Initiating Remote Mass Erase
 CS\_DAP\_0: GEL Output: Mass Erase Command Sent
 CS\_DAP\_0: GEL Output: Press the reset button...

6. After pressing the reset button, the Console will show the following:

Source 
 Source