



## WEBENCH® Design Report







Design : 4211465/4 LM3401MM/NOPB  
LM3401MM/NOPB 24.0V-32.0V to 18.60V @ 0.72A










## Electrical BOM







#	Name	Manufacturer	Part Number	Properties	Qty	Price	Footprint
1.	Cin	MuRata	GRM31CR71H475KA12L Series= X7R	Cap= 4.7 uF ESR= 3.0 mOhm VDC= 50.0 V IRMS= 4.98 A	1	\$0.07	 1206 11 mm <sup>2</sup>
2.	Cout	TDK	C3225X7S2A475M Series= 479	Cap= 4.7 uF ESR= 4.547 mOhm VDC= 100.0 V IRMS= 0.0 A	1	\$0.42	 1210 15 mm <sup>2</sup>
3.	D1	NXP Semiconductor	PMEG6010CEH,115	VF@Io= 570.0 mV VRRM= 60.0 V	1	\$0.11	 SOD-123F 12 mm <sup>2</sup>
4.	D_LED	Citizen Electronics	CL-L233-C13N1-C	LED	1	NA	 CIT_LED_5 501 mm <sup>2</sup>
5.	L1	Bourns	SDR0604-180YL	L= 18.0 uH DCR= 150.0 mOhm	1	\$0.18	 SDR0604 61 mm <sup>2</sup>
6.	M1	Vishay-Siliconix	SI2319DS-T1-E3	VdsMax= -40.0 V IdsMax= -2.3 Amps	1	\$0.28	 SOT-23 14 mm <sup>2</sup>
7.	Rhys	Panasonic	ERJ-6ENF1402V Series= 225	Res= 14.0 kOhm Power= 125.0 mW Tolerance= 1.0%	1	\$0.01	 0805 7 mm <sup>2</sup>
8.	Rilim	Panasonic	ERJ-6ENF3832V Series= 225	Res= 38.3 kOhm Power= 125.0 mW Tolerance= 1.0%	1	\$0.01	 0805 7 mm <sup>2</sup>
9.	Rsense	Panasonic	ERJ-8RQFR27V Series= 229	Res= 270.0 mOhm Power= 250.0 mW Tolerance= 1.0%	1	\$0.04	 1206 11 mm <sup>2</sup>







#	Name	Manufacturer	Part Number	Properties	Qty	Price	Footprint
10.	U1	Texas Instruments	LM3401MM/NOPB	Switcher	1	\$0.60	 MUA08A 24 mm <sup>2</sup>














## Operating Values

#	Name	Value	Category	Description
1.	Cin IRMS	248.073 mA	Current	Input capacitor RMS ripple current
2.	Cout IRMS	143.344 mA	Current	Output capacitor RMS ripple current
3.	Iin Avg	447.54 mA	Current	Average input current
4.	L Ipp	496.56 mA	Current	Peak-to-peak inductor ripple current
5.	L1 Irms	734.13 mA	Current	Inductor ripple current
6.	LED Iavg	740.741 mA	Current	LED Average Current
7.	LED Ipp	118.826 mA	Current	LED Ripple Current
8.	M Irms	689.923 mA	Current	MOSFET RMS ripple current
9.	SW Ipk	0.0 A	Current	Peak switch current
10.	BOM Count	10	General	Total Design BOM count
11.	FootPrint	661.0 mm <sup>2</sup>	General	Total Foot Print Area of BOM components
12.	Frequency	875.0 kHz	General	Switching frequency
13.	IC Tolerance	12.0 mV	General	IC Feedback Tolerance
14.	M Rdson	130.0 mOhm	General	Drain-Source On-resistance
15.	M Vds Act	89.69 mV	General	M Vds
16.	Pout	13.536 W	General	Total output power
17.	Total BOM	\$0.0	General	Total BOM Cost
18.	D1 Tj	67.888 degC	Op_Point	D1 junction temperature
19.	Vout OP	18.8 V	Op_Point	Operational Output Voltage
20.	Duty Cycle	59.248 %	Op_point	Duty cycle
21.	Efficiency	94.516 %	Op_point	Steady state efficiency
22.	IC Tj	30.0 degC	Op_point	IC junction temperature
23.	ICThetaJA	151.0 degC/W	Op_point	IC junction-to-ambient thermal resistance
24.	IOUT_OP	720.0 mA	Op_point	Iout operating point
25.	LED Rd	1.65 Ohm	Op_point	LED DynamicResistance
26.	LED Vf	18.6 V	Op_point	Total LED Forward Calculated Voltage
27.	M ThetaJA	120.0 degC/W	Op_point	MOSFET junction-to-ambient thermal resistance
28.	M TjOp	54.58 degC	Op_point	MOSFET junction temperature
29.	VIN_OP	32.0 V	Op_point	Vin operating point
30.	Cin Pd	184.62 μW	Power	Input capacitor power dissipation
31.	Cout Pd	93.429 μW	Power	Output capacitor power dissipation
32.	Diode Pd	114.813 mW	Power	Diode power dissipation
33.	IC Pd	240.0 mW	Power	IC power dissipation
34.	L Pd	85.536 mW	Power	Inductor power dissipation
35.	LED Pd	13.392 W	Power	LED Power Dissipation
36.	M Pd	204.835 mW	Power	MOSFET power dissipation
37.	M1 PdCond	71.69 mW	Power	M1 MOSFET conduction losses
38.	M1 PdSw	133.145 mW	Power	M1 MOSFET switching losses
39.	Rsense Pd	139.968 mW	Power	LED Current Rsns Power Dissipation
40.	Total Pd	785.379 mW	Power	Total Power Dissipation

## Design Inputs

#	Name	Value	Description
1.	Iout	720.0 m	Maximum Output Current
2.	Iout1	720.0 m	Output Current #1
3.	VinMax	32.0	Maximum input voltage
4.	VinMin	24.0	Minimum input voltage
5.	Vout	18.6	Output Voltage
6.	Vout1	18.6	Output Voltage #1
7.	application	LED_DRIVER	LED Application
8.	base_pn	LM3401	Base Product Number

#	Name	Value	Description
9.	LED_Architect	N	LED Architect Project
10.	ledparallel	1.0	Number of LED in parallel
11.	ledpartnumber	CL-L233-C13N1-C	LED Part number
12.	ledseries	1.0	Number of LED in series
13.	line_fsw	60.0	AC Line Frequency
14.	source	DC	Input Source Type
15.	Ta	30.0	Ambient temperature

## Design Assistance

1. **LM3401** Product Folder : <http://www.ti.com/product/LM3401> : contains the data sheet and other resources.

Texas Instruments' WEBENCH simulation tools attempt to recreate the performance of a substantially equivalent physical implementation of the design. Simulations are created using Texas Instruments' published specifications as well as the published specifications of other device manufacturers. While Texas Instruments does update this information periodically, this information may not be current at the time the simulation is built. Texas Instruments does not warrant the accuracy or completeness of the specifications or any information contained therein. Texas Instruments does not warrant that any designs or recommended parts will meet the specifications you entered, will be suitable for your application or fit for any particular purpose, or will operate as shown in the simulation in a physical implementation. Texas Instruments does not warrant that the designs are production worthy.

**You should completely validate and test your design implementation to confirm the system functionality for your application prior to production.**

Use of Texas Instruments' WEBENCH simulation tools is subject to [Texas Instruments' Site Terms and Conditions of Use](#). Prototype boards based on WEBENCH created designs are provided AS IS without warranty of any kind for evaluation and testing purposes and are subject to the terms of the [Evaluation License Agreement](#).